

# Maximum loading of automatic circuit breakers



## Amy

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [μs]
96665583	AMY 100 LED DL 800 830	176	229	282	352	438	106	138	170	212	264	15	50
96665584	AMY 100 LED DL 800 840	176	229	282	352	438	106	138	170	212	264	15	50
96628352	AMY 150 LED DL 1000 830	132	172	211	264	330	80	103	127	159	200	15	50
96628353	AMY 150 LED DL 1000 840	132	172	211	264	330	80	103	127	159	200	15	50
96665585	AMY 150 LED DL 1500 830	99	129	158	198	330	60	78	95	119	200	15	50
96665586	AMY 150 LED DL 1500 840	99	129	158	198	330	60	78	95	119	200	15	50
96665587	AMY 200 LED DL 2000 830	75	98	120	150	250	45	59	72	90	150	20	50
96665588	AMY 200 LED DL 2000 840	75	98	120	150	250	45	59	72	90	150	20	50
96665848	AMY 150 LED DL 1000 830 E3	132	172	211	264	250	80	103	127	159	150	20	50
96665849	AMY 150 LED DL 1000 840 E3	132	172	211	264	250	80	103	127	159	150	20	50
96665844	AMY 150 LED DL 1500 830 E3	99	129	158	198	188	60	78	95	119	113	20	50
96665845	AMY 150 LED DL 1500 840 E3	99	129	158	198	188	60	78	95	119	113	20	50
96665846	AMY 200 LED DL 2000 830 E3	75	98	120	150	188	45	59	72	90	113	20	50
96665847	AMY 200 LED DL 2000 840 E3	75	98	120	150	188	45	59	72	90	113	20	50



## Amy Vario

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [ms]
96632753	AMY VARIO 100 LED DL 700 830/35/40	40	53	65	81	96	37	48	59	74	92	0.14	140
96632754	AMY VARIO 150 LED DL 1000 830/35/40	31	41	50	63	78	28	37	46	57	70	0.18	280
96632755	AMY VARIO 150 LED DL 1500 830/35/40	27	35	43	54	67	24	32	39	49	61	0.21	780
96632756	AMY VARIO 200 LED DL 2000 830/35/40	20	26	32	40	50	18	24	29	37	47	0.28	640




## Anna

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [μs]
96630066	ANNA LED Q596 3750 840	27	35	44	54	18	24	30	36	20	260
96630067	ANNA LED Q622 3750 840	27	35	44	54	18	24	30	36	20	260
96630068	ANNA LED Q596 3750 840 E3	27	35	44	54	18	24	30	36		
96630069	ANNA LED Q596 3400 830	27	35	44	54	18	24	30	36	20	260
96630070	ANNA LED Q622 3400 830	27	35	44	54	18	24	30	36	20	260
96630359	ANNA LED Q596 3600 840-TpA	27	35	44	54	18	24	30	36		
96630360	ANNA LED Q596 3600 840-TPA E3	27	35	44	54	18	24	30	36		
96631113	ANNA LED Q596 3750 840 HFIX	27	35	44	54	18	24	30	36	28	195
96631114	ANNA LED Q622 3750 840 HFIX	27	35	44	54	18	24	30	36	28	195
96631115	ANNA LED Q596 3750 840 HFIX E3	27	35	44	54	18	24	30	36	28	195
96631116	ANNA LED Q596 3400 830 HFIX	27	35	44	54	18	24	30	36	28	195
96631117	ANNA LED Q622 3400 830 HFIX	27	35	44	54	18	24	30	36	28	195
96631118	ANNA LED Q596 3600 840 HFIX TpA	27	35	44	54	18	24	30	36		
96631119	ANNA LED Q596 3600 840 HFIX TpA E3	27	35	44	54	18	24	30	36		
96631380	ANNA LED 1200x300 4400 840	18	24	30	35	12	16	20	23	30	270
96631381	ANNA LED 1200x300 4000 830	18	24	30	35	12	16	20	23	30	270



## Anna Vario

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [μs]
96634037	ANNA VARIO 1200X300 4000 830/35/40	27	35	43	54	67	19	24	30	38	47	22	200
96634045	ANNA VARIO 1200X300 4000 830/35/40 HFIX	34	44	54	68	85	34	44	54	68	85	10	50
96634030	ANNA VARIO Q596 3000 830/35/40	34	44	55	68	85	24	31	38	48	60	18	220
96634032	ANNA VARIO Q596 3750 830/35/40	27	35	43	54	67	19	24	30	38	47	22	200
96634034	ANNA VARIO Q596 3750 830/35/40 HFIX	34	44	54	68	85	34	44	54	68	85	10	50
96634035	ANNA VARIO Q622 3750 830/35/40	27	35	43	54	67	19	24	30	38	47	22	200
96634036	ANNA VARIO Q622 3750 830/35/40 HFIX	34	44	54	68	85	34	44	54	68	85	10	50



# Boris

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96634055	BORIS 300 13000 840	5	6	8	10	13	5	6	8	10	13	80	150
96634056	BORIS 300 19000 840	4	5	7	8	11	3	4	6	7	11	100	220
96634057	BORIS 375 25000 840	3	4	5	6	8	3	4	5	6	8	100	220
96634058	BORIS 375 30000 840	2	3	4	5	6	2	3	4	5	6	100	316



# Elsa

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96630327	ELSA LED 600 1200 840 WH	80	100	125	160	80	100	125	160	60	350
96630328	ELSA LED 600 1200 830 WH	80	100	125	160	80	100	125	160	60	350
96630329	ELSA LED 600 1200 840 MWS WH	80	100	125	160	80	100	125	160	60	350
96630330	ELSA LED 600 1200 830 MWS WH	80	100	125	160	80	100	125	160	60	350
96630376	ELSA LED 450 800 840 WH	80	100	125	160	80	100	125	160	60	350
96630377	ELSA LED 450 800 830 WH	80	100	125	160	80	100	125	160	60	350
96630378	ELSA LED 450 800 840 MWS WH	80	100	125	160	80	100	125	160	60	350
96630379	ELSA LED 450 800 830 MWS WH	80	100	125	160	80	100	125	160	60	350



# Emma

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96629751	EMMA LED 1500 6000 830	41	53	65	82	103	41	53	65	82	103	15	100
96666099	EMMA LED 1500 6000 840	41	53	65	82	103	41	53	65	82	103	15	100
96629750	EMMA LED 1200 4000 830	30	39	48	60	75	30	39	48	60	75	5.5	20
96666098	EMMA LED 1200 4000 840	30	39	48	60	75	30	39	48	60	75	5.5	20
96666100	EMMA LED 600 2000 840	60	78	96	120	150	60	78	96	120	150	6.1	18
96630322	EMMA LED 600 2000 830	60	78	96	120	150	60	78	96	120	150	6.1	18



## Fred

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96630340	FRED LED IP65 75 550 840	166	216	266	333	416	150	200	250	320	416	1.92	40
96630341	FRED LED IP65 75 550 830	166	216	266	333	416	150	200	250	320	416	1.92	40



## George

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96630323	GEORGE LED 330 12000 840	17	22	22	34	43	8	8	13	17	21	75	
96630324	GEORGE LED 330 18000 840	5	6	6	10	12	2	2	4	5	6	75	
96630325	GEORGE LED 390 24000 840	5	6	6	10	12	2	2	4	5	6	75	
96630326	GEORGE LED 390 30000 840	3	4	4	7	9	1	1	3	3	4	75	



## Holly

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96633683	HOLLY CONE ROUND DOWN IP65 300 830	56	68	82	96	44	54	65	76	30	200
96633684	HOLLY CONE ROUND UP/DOWN IP65 500 830	56	68	82	96	44	54	65	76	30	200
96633685	HOLLY CONE SQUARE DOWN IP65 300 830	56	68	82	96	44	54	65	76	30	200
96633686	HOLLY CONE SQUARE UP/DOWN IP65 500 830	56	68	82	96	44	54	65	76	30	200
96633687	HOLLY WALL CAN DOWN IP65 250 830	56	68	82	96	44	54	65	76	30	200



# Julie

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96628548	JULIE 600 LED IP65 2200 840	50	70	80	110	150	20	75	115	125	110	15	100
96631255	JULIE 1200 LED IP65 3200 840	60	80	90	110	140	50	70	80	100	110	15	100
96631404	JULIE 1200 LED IP65 3200 840 E3	60	80	90	110	140	50	70	80	100	110	15	100
96665578	JULIE 1200 LED IP65 4200 840 CONNECT	45	65	70	90	100	40	60	60	80	100	15	100
96665577	JULIE 1200 LED IP65 4200 840	45	65	70	90	100	40	60	60	80	100	15	100
96665579	JULIE 1200 LED IP65 4200 840 E3	45	65	70	90	100	40	60	60	80	100	15	100
96630234	JULIE 1200 LED IP65 4200 840 COR MWS	45	65	70	90	100	40	60	60	80	100	15	100
96630237	JULIE 1200 LED IP65 4200 840 COR MWS CON	45	65	70	90	100	40	60	60	80	100	15	100
96630239	JULIE 1200 LED IP65 4200 840 TW	45	65	70	90	100	40	60	60	80	100	15	100
96631093	JULIE 1200 LED IP65 4200 840 COR MWS E3	45	65	70	90	100	40	60	60	80	100	15	100
96628396	JULIE 1500 LED IP65 4200 840	45	65	70	90	100	40	60	60	80	100	15	100
96628397	JULIE 1500 LED IP65 4200 840 E3	45	65	70	90	100	40	60	60	80	100	15	100
96630235	JULIE 1500 LED IP65 4200 840 COR MWS	45	65	70	90	100	40	60	60	80	100	15	100
96631094	JULIE 1500 LED IP65 4200 840 COR MWS E3	45	65	70	90	100	40	60	60	80	100	15	100
96630240	JULIE 1500 LED IP65 4200 840 TW	45	65	70	90	100	40	60	60	80	100	15	100
96628449	JULIE 1500 LED 50°C IP65 4200 840	45	65	70	90	100	40	60	60	80	100	15	100
96630351	JULIE 1500 LED 50°C IP65 6300 840	30	45	50	60	100	40	60	60	80	100	15	100
96665580	JULIE 1500 LED IP65 6300 840	30	45	50	60	75	30	45	50	60	75	15	100
96665581	JULIE 1500 LED IP65 6300 840 CONNECT	30	45	50	60	75	30	45	50	60	75	15	100
96665582	JULIE 1500 LED IP65 6300 840 E3	30	45	50	60	75	30	45	50	60	75	15	100
96630236	JULIE 1500 LED IP65 6300 840 COR MWS	30	45	50	60	75	30	45	50	60	75	15	100
96630238	JULIE 1500 LED IP65 6300 840 COR MWS CON	30	45	50	60	75	30	45	50	60	75	15	100
96631095	JULIE 1500 LED IP65 6300 840 COR MWS E3	30	45	50	60	75	30	45	50	60	75	15	100
96630241	JULIE 1500 LED IP65 6300 840 TW	30	45	50	60	75	30	45	50	60	75	15	100
96631143	JULIE 1800 LED IP65 8600 840	20	30	35	45	50	20	30	30	40	50	20	100
96631144	JULIE 1800 LED IP65 8600 840 E3	20	30	35	45	50	20	30	30	40	50	20	100
96631300	JULIE 1800 LED IP65 8600 840 CONNECT	20	30	35	45	50	20	30	30	40	50	20	100



# Lara

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [μs]
96666101	LARA LED 250 800 840 WH	64	83	105	128	161	39	50	62	77	96	8.5	220
96666102	LARA LED 250 800 840 BLK	64	83	105	128	161	39	50	62	77	96	8.5	220
96666103	LARA LED 250 800 840 WH E3	64	83	105	128	161	56	72	90	112	96	8.5	220
96666104	LARA LED 250 800 840 BLK E3	64	83	105	128	161	39	50	62	77	96	8.5	220
96666109	LARA LED 250 800 840 MWS WH	64	83	105	128	161	39	50	62	77	96	8.5	220
96666110	LARA LED 250 800 840 MWS BLK	64	83	105	128	161	39	50	62	77	96	8.5	220
96666111	LARA LED 250 800 840 MWS WH E3	64	83	105	128	161	39	50	62	77	96	8.5	220
96666112	LARA LED 250 800 840 MWS BLK E3	64	83	105	128	161	39	50	62	77	96	8.5	220
96666117	LARA LED 250 800 840 PC WH	64	83	105	128	161	39	50	62	77	96	8.5	220
96666118	LARA LED 250 800 840 PC BLK	64	83	105	128	161	39	50	62	77	96	8.5	220
96666105	LARA LED 300 1200 840 WH	93	121	153	187	234	56	72	90	112	140	3.2	32
96666106	LARA LED 300 1200 840 BLK	93	121	153	187	234	56	72	90	112	140	3.2	32
96666107	LARA LED 300 1200 840 WH E3	93	121	153	187	234	56	72	90	112	140	3.2	32
96666108	LARA LED 300 1200 840 BLK E3	93	121	153	187	234	56	72	90	112	140	3.2	32
96666113	LARA LED 300 1200 840 MWS WH	93	121	153	187	234	56	72	90	112	140	3.2	32
96666114	LARA LED 300 1200 840 MWS BLK	93	121	153	187	234	56	72	90	112	140	3.2	32
96666115	LARA LED 300 1200 840 MWS WH E3	93	121	153	187	234	56	72	90	112	140	3.2	32
96666116	LARA LED 300 1200 840 MWS BLK E3	93	121	153	187	234	56	72	90	112	140	3.2	32
96666119	LARA LED 300 1200 840 PC BLK	93	121	153	187	234	56	72	90	112	140	3.2	32
96666120	LARA LED 300 1200 840 PC WH	93	121	153	187	234	56	72	90	112	140	3.2	32
96629752	LARA LED 330 2000 840 WH	45	60	75	90	113	36	48	60	72	92	10	100
96629754	LARA LED 330 2000 840 MWS WH	45	60	75	90	113	36	48	60	72	92	10	100
96629755	LARA LED 330 2000 840 WH E3	45	60	75	90	113	36	48	60	72	92	10	100
96629756	LARA LED 330 2000 840 MWS WH E3	45	60	75	90	113	36	48	60	72	92	10	100



# Lena Vario

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [ms]
96631862	LENA VARIO LED 320 1400 830/35/40	11	14	18	22	28	10	13	16	20	25	0.50	90
96631863	LENA VARIO LED 320 1400 830/35/40 MWS	7	10	12	15	18	6	9	11	13	17	0.76	420

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [ms]
96631864	LENA VARIO LED 380 1900 830/35/40	19	24	30	38	47	17	22	27	34	43	0.30	90
96631865	LENA VARIO LED 380 1900 830/35/40 MWS	18	23	28	35	44	16	21	26	32	39	0.32	550
96631866	LENA VARIO LED 380 2500 830/35/40	15	19	24	30	37	13	17	22	27	33	0.38	280
96631867	LENA VARIO LED 380 2500 830/35/40 MWS	14	18	22	28	35	13	17	20	26	32	0.40	550



## Leo

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [μs]
96632698	LEO LED FL IP66 75W 830 PC	26	34	42	54	13	17	21	27	40	100
96632699	LEO LED FL IP66 100W 830 PC	8	12	16	20	4	6	8	10	40	100
96632700	LEO LED FL IP66 150W 830 PC	6	8	10	12	3	4	5	6	75	650
96632701	LEO LED FL IP66 200W 830 PC	4	6	8	10	2	3	4	5	75	600
96632702	LEO LED FL IP66 210W 830 PC	4	6	8	10	2	3	4	5	75	600
96630252	LEO LED FL IP66 75W 840 PC	26	34	42	54	13	17	21	27	40	100
96630253	LEO LED FL IP66 100W 840 PC	8	12	16	20	4	6	8	10	40	100
96630254	LEO LED FL IP66 150W 840 PC	6	8	10	12	3	4	5	6	75	650
96630255	LEO LED FL IP66 200W 840 PC	4	6	8	10	2	3	4	5	75	600
96630256	LEO LED FL IP66 210W 840 PC	4	6	8	10	2	3	4	5	75	600



## Leonie

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [μs]
96630335	LEONIE LED FL IP65 10W 840	147	190	234	354	73	95	117	147	30	26
96630336	LEONIE LED FL IP65 20W 840	176	228	280	352	88	114	140	176	30	33
96630337	LEONIE LED FL IP65 30W 840	116	140	186	234	58	70	93	117	30	33
96630338	LEONIE LED FL IP65 50W 840	70	90	112	140	35	45	56	70	30	33
96631096	LEONIE LED FL IP65 10W 830	147	190	234	354	73	95	117	147	30	26
96631097	LEONIE LED FL IP65 20W 830	176	228	280	352	88	114	140	176	30	33
96631098	LEONIE LED FL IP65 30W 830	116	140	186	234	58	70	93	117	30	33
96631099	LEONIE LED FL IP65 50W 830	70	90	112	140	35	45	56	70	30	33



# Lily

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96632287	LILY LED SPOT IP44 38° 68 550 930 ADJ WH	221	287	362	443	134	172	213	266	30	350
96632288	LILY LED SPOT IP44 38° 68 550 940 ADJ WH	221	287	362	443	134	172	213	266	30	350
96632290	LILY LED SPOT IP44 38° 68 850 930 ADJ WH	221	287	362	443	134	172	213	266	30	350
96632291	LILY LED SPOT IP44 38° 68 850 940 ADJ WH	221	287	362	443	134	172	213	266	30	350
96633274	LILY LED SPOT IP44 24° 68 600 927	221	287	362	443	134	172	213	266	30	350
96633275	LILY LED SPOT IP44 24° 68 600 930	221	287	362	443	134	172	213	266	30	350
96633276	LILY LED SPOT IP44 24° 68 600 940	221	287	362	443	134	172	213	266	30	350
96633277	LILY LED SPOT IP44 24° 68 850 927	221	287	362	443	134	172	213	266	30	350
96633278	LILY LED SPOT IP44 24° 68 850 930	221	287	362	443	134	172	213	266	30	350
96633279	LILY LED SPOT IP44 24° 68 850 940	221	287	362	443	134	172	213	266	30	350
96633280	LILY LED SPOT IP44 38° 68 600 927	221	287	362	443	134	172	213	266	30	350
96633281	LILY LED SPOT IP44 38° 68 600 930	221	287	362	443	134	172	213	266	30	350
96633282	LILY LED SPOT IP44 38° 68 600 940	221	287	362	443	134	172	213	266	30	350
96633283	LILY LED SPOT IP44 38° 68 850 927	221	287	362	443	134	172	213	266	30	350
96633284	LILY LED SPOT IP44 38° 68 850 930	221	287	362	443	134	172	213	266	30	350
96633285	LILY LED SPOT IP44 38° 68 850 940	221	287	362	443	134	172	213	266	30	350
96633286	LILY LED SPOT IP44 60° 68 600 927	221	287	362	443	134	172	213	266	30	350
96633287	LILY LED SPOT IP44 60° 68 600 930	221	287	362	443	134	172	213	266	30	350
96633288	LILY LED SPOT IP44 60° 68 600 940	221	287	362	443	134	172	213	266	30	350
96633289	LILY LED SPOT IP44 60° 68 850 927	221	287	362	443	134	172	213	266	30	350
96633290	LILY LED SPOT IP44 60° 68 850 930	221	287	362	443	134	172	213	266	30	350
96633291	LILY LED SPOT IP44 60° 68 850 940	221	287	362	443	134	172	213	266	30	350



# Lucy

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96630331	LUCY 600 LED IP66 2000 840 TW	75	115	125	150	210	50	70	80	110	110	15	100
96630332	LUCY 1200 LED IP66 4000 840 TW	45	65	70	90	100	40	60	60	80	100	15	100
96630333	LUCY 1500 LED IP66 6000 840 TW	30	45	50	60	75	30	45	50	60	75	15	100
96630334	LUCY 1800 LED IP66 8000 840 TW	22	32	35	45	50	20	30	30	40	50	30	100





# Mary

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96633583	MARY LED GARDEN SPOT IP65 500 830	56	68	82	96	44	54	65	76	15	200



# Poppy

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96631257	POPPY LED 600 2500 840	75	115	125	150	210	50	70	80	110	110	15	100
96631258	POPPY LED 1200 2500 840	75	115	125	150	210	50	70	80	110	110	15	100
96631259	POPPY LED 1200 5000 840	35	50	60	75	80	35	50	55	70	80	15	100
96631260	POPPY LED 1500 4500 840	45	65	70	90	100	40	60	60	80	100	15	100
96631261	POPPY LED 1500 6500 840	30	45	50	60	75	30	45	50	60	75	15	100
96631262	POPPY LED 1800 6500 840	30	45	50	60	75	30	45	50	60	75	15	100
96631263	POPPY LED 1800 8500 840	20	30	35	45	50	20	30	30	40	50	20	100
96631268	POPPY LED 1200 2500 840 E3	75	115	125	150	210	50	70	80	110	110	15	100
96631269	POPPY LED 1200 5000 840 E3	35	50	60	75	80	35	50	55	70	80	15	100
96631270	POPPY LED 1500 4500 840 E3	45	65	70	90	100	40	60	60	80	100	15	100
96631271	POPPY LED 1500 6500 840 E3	30	45	50	60	75	30	45	50	60	75	15	100
96631272	POPPY LED 1800 6500 840 E3	30	45	50	60	75	30	45	50	60	75	15	100
96631273	POPPY LED 1800 8500 840 E3	20	30	35	45	50	20	30	30	40	50	20	100
96633168	POPPY LED 1500 4500 840 PIR	45	65	70	90	100	40	60	60	80	100	15	100
96633170	POPPY LED 1500 4500 840 PIR E3	45	65	70	90	100	40	60	60	80	100	15	100
96633169	POPPY LED 1500 6500 840 PIR	30	45	50	60	75	30	45	50	60	75	15	100
96633171	POPPY LED 1500 6500 840 PIR E3	30	45	50	60	75	30	45	50	60	75	15	100



# Rosy

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96633582	ROSY LED INGROUND IP67 200 830	56	68	82	96	44	54	65	76	15	200



# Roxy

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96634867	ROXY 1200 D 4000 840 FLEX	29	38	47	59	74	20	27	33	41	52	17	220
96634868	ROXY 1200 D 4000 840 HFIX	21	28	35	45	56	13	17	21	27	33	35	170
96634869	ROXY 1500 D 5500 840 FLEX	20	26	32	40	50	14	18	22	28	35	23	235
96634870	ROXY 1500 D 5500 840 HFIX	21	28	35	45	56	13	17	21	27	33	35	170
96634871	ROXY 1200 D/I 5500 840 FLEX	20	26	32	40	50	14	18	22	28	35	23	235
96634872	ROXY 1200 D/I 5500 840 HFIX	21	28	35	45	56	13	17	21	27	33	35	170
96634873	ROXY 1200 ASYM 2000 840	51	67	83	103	129	31	40	49	62	77	13	180
96634874	ROXY 1200 ASYM 2000 840 HFIX	30	38	46	58	72	18	23	28	35	43	13.6	304



# Tom

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96666080	TOM LED 300 1200 840 WH	70	91	112	141	66	86	106	133		
96666081	TOM LED 300 1200 840 BLK	70	91	112	141	66	86	106	133		
96666082	TOM LED 300 1200 840 MWS WH	63	82	101	126	60	78	96	120		
96666083	TOM LED 300 1200 840 MWS BLK	63	82	101	126	60	78	96	120		
96666084	TOM LED EYE 300 900 840 WH	70	91	112	141	66	86	106	133		
96666085	TOM LED EYE 300 900 840 BLK	70	91	112	141	66	86	106	133		
96666086	TOM LED EYE 300 900 840 MWS WH	63	82	101	126	60	78	96	120		
96666087	TOM LED EYE 300 900 840 MWS BLK	63	82	101	126	60	78	96	120		



# Tom Vario

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96668718	TOM VARIO LED 300 1200 830/40 BK	90	120	160	210	260	50	70	90	110	150	12	100
96668719	TOM VARIO LED 300 1200 830/40 MWS BK	90	120	160	210	260	50	70	90	110	150	12	100
96632237	TOM VARIO LED 300 1200 830/40 WH	90	120	160	210	260	50	70	90	110	150	12	100
96632238	TOM VARIO LED 300 1200 830/40 MWS WH	90	120	160	210	260	50	70	90	110	150	12	100
96631714	TOM VARIO LED 300 2000 830/40 WH	75	115	125	150	150	50	70	80	110	110	15	100
96631715	TOM VARIO LED 300 2000 830/40 MWS WH	75	115	125	150	150	50	70	80	110	110	15	100
96668716	TOM VARIO LED 300 2000 830/40 BK	75	115	125	150	150	50	70	80	110	110	15	100
96668717	TOM VARIO LED 300 2000 830/40 MWS BK	75	115	125	150	150	50	70	80	110	110	15	100



# Zoe

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current [A]	Pulse duration [µs]
96666088	ZOE LED DL 110 600 840	198	257	317	396	119	155	191	239		
96666089	ZOE LED DL 160 900 840	132	172	211	264	80	103	127	159		
96666090	ZOE LED DL 210 1500 840	88	114	141	176	53	69	85	106		
96666092	ZOE LED DL 110 600 830	198	257	317	396	119	155	191	239		
96666093	ZOE LED DL 160 900 830	132	172	211	264	80	103	127	159		
96666094	ZOE LED DL 210 1500 830	88	114	141	176	53	69	85	106		
96666091	ZOE LED DL 210 2000 840	72	94	115	144	43	56	69	87		
96666095	ZOE LED DL 210 2000 830	72	94	115	144	43	56	69	87		



# Zoe Vario

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current [A]	Pulse duration [µs]
96632685	ZOE VARIO LED DL 130 700 830/35/40	120	156	193	240	303	82	107	132	165	202	11	200
96632686	ZOE VARIO LED DL 170 1000 830/35/40	80	104	129	161	201	55	71	88	110	141	13	220
96632687	ZOE VARIO LED DL 210 1600 830/35/40	52	68	85	107	133	36	47	58	73	93	15	220
96632688	ZOE VARIO LED DL 210 2000 830/35/40	43	57	70	87	110	30	39	48	60	77	16	220